SHORELINE PRODUCTS Ltd.

European Shoreline User Guidlines

The European Shoreline is designed with safety and durability as the top priority. Available in various lengths and with a clear label to carry the name of your vessel, a contact phone number etc.

Installation safety

Always ensure the power is switched off at the marina supply before connecting or disconnecting the shoreline. Make sure the connectors are clean and dry before connecting.

This may seem obvious but… in order to completely remove the risk of dropping a live shoreline into the water…

Connect --- boat end first

When connecting... connect to the boat end first, marina end last…

Disconnect ---marina end first

When disconnecting… disconnect from the marina supply socket first, boat end last

Status Monitor (where fitted)

If you have the Safety Shoreline with built in status indicator you will be warned if the marina power outlet is incorrectly wired as follows.

the only correct indication is 2 greens. ANY OTHER COMBINATION MEANS THE SHORE SUPPLY IS INCORRECTLY WIRED...DO NOT USE...

PLUG END..... CABLE END

off.....off.....off power switched off (or no Live)

green....off.....green CORRECT....OK

green....red.....off INCORRECT (Line and Neutral reversed...)

green....red.....green INCORRECT (No earth or no neutral...)

Specification

connectors; 240V 16 Amp 1 phase and earth, blue IEC 60309, IP44 suitable for use on pleasure craft in marinas as specified in BS7671:2008 section 709

cable; BS6500 2,5 square millimetre, 25 Amp current rating, 3 core, blue, Arctic grade (-20 to +70 deg C ambient temp rating) available in standard lengths of 10, 15 or 25 metres, or to order.

status indicator, (where fitted)
a status indicator fitted into the plug checks the wiring of the socket into which it is plugged (e.g. the power outlet on the marina tower) and warns of incorrect wiring via 3 LEDs (2 green 1 red)

power consumption of the status indicator is less than 0.2 watts, 220V a.c. 50 Hz

……

E and OE Shoreline products Ltd. December 2009